

Drives - Model Series RGLB, RPBL, PGBL and Blower Cabinet RBL

Drive Components for Open Motors

Unit Size	Open Motor		Voltage Option	Drive AM Nos. (See Key, page 35)	Motor Pulley			Blower Pulley			Belt			*Shaft Centerline
	HP	Opt			P/N	Mfr #	Bore	P/N	Mfr No.	Bore	P/N	Qty	Mfr #	
All "BL" Units	1	AL6	AK1 (115/1); AK2 (208/1); AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3)	AM 2, 3, 4	13580	1VL34	5/8	111862	AK84	1-3/16	16134	1	A57	20.94
				AM 5, 6, 7	13580	1VL34	5/8	105484	AK71H ^A	1-3/16	16134	1	A57	21.03
				AM 2, 3, 4			7/8				16134	1	A57	20.94
				AM 5, 6, 7			7/8				16134	1	A57	21.03
	1-1/2	AL7	AK1 (115/1); AK2 (208/1); AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3)	AM 3, 4, 5, 6, 7	13580	1VL34	5/8	105484	AK71H ^A	1-3/16	16134	1	A57	21.03
				AM 8, 9, 10, 11	105476	1VL44	5/8	106256	AK74	1-3/16	16134	1	A57	21.11
				AM 3, 4, 5, 6, 7			7/8				16134	1	A57	21.03
				AM 8, 9, 10, 11			7/8				16134	1	A57	21.11
	2	AL8	AK1 (115/1); AK2 (208/1); AK3 (230/1)	AM 3, 4, 5, 6, 7			5/8				16132	1	A55	20.03
				AM 8, 9, 10, 11			5/8				16133	1	A56	20.85
				AM 12, 13, 14, 15, 16			5/8				16131	1	A54	21.07
				AM 3, 4, 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^A	1-3/16	16132	1	A55	20.03
	2	AL8	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 8, 9, 10, 11	106758	1VL44	7/8	105484	AK71H ^A	1-3/16	16133	1	A56	20.85
				AM 12, 13, 14, 15, 16	106758	1VL44	7/8	110807	AK56H ^A	1-3/16	16131	1	A54	21.07
				AM 7, 8, 9			5/8				92264	1	A78	20.95
				AM 10, 11, 12, 13			5/8				16558	1	A69	20.96
	3	AL9	AK2 (208/1); AK3 (230/1)	AM 14, 15, 16, 17, 18			5/8				111870	1	A66	20.92
				AM 7, 8, 9	37451	1VM50	7/8	16160	AK184	1-3/16	92264	1	A78	20.95
				AM 10, 11, 12, 13	106758	1VL44	7/8	16158	AK134	1-3/16	16558	1	A69	20.96
				AM 14, 15, 16, 17, 18	37451	1VM50	7/8	16156	AK124	1-3/16	111870	1	A66	20.92
	5	AL10	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 8,9,10,11	6599	2VP42	7/8	16161	2AK134	1-3/16	92408	1	A68	21.08
				AM 12,13,14,15	87500	2VP36	7/8	16003	2BK100	1-3/16	88560	1	A61	21.01
				AM 16, 17, 18, 19, 20	6599	2VP42	7/8	16003	2BK100	1-3/16	16137	1	A62	21.08
				AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47
	7-1/2	AL11	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31
				AM 14, 15, 16	16150	2VP62	1-3/8	91633	2TB86 ^B	1-3/16	92280	1	BX59	20.47
				AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^A	1-3/16	92280	1	BX59	20.37
				AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47
10	AL12	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31	
			AM 14,15,16	16150	2VP62	1-3/8	91633	2TB86 ^B	1-3/16	92280	1	BX59	20.47	
			AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^A	1-3/16	92280	1	BX59	20.37	
			AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47	
**15	AL15	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 17, 18, 19, 20	89644	3MVP40-B54	1-5/8	106258	3TB66H ^G	1-7/16	92224	1	B56	20.47	
			AM 21, 22, 23, 24	89644	3MVP40-B54	1-5/8	106262	3BK65H ^C	1-7/16	92224	1	B56	20.53	
			AM 17, 18, 19, 20, 21, 22, 23, 24	89644	3MVP40-B54	1-5/8	106262	3BK65H ^C	1-7/16	92239	1	BX54	20.11	
			AM 15, 16, 17	148593 ^E	2MVP70B84P	1-5/8"	113811	2BK120H ^D	1-7/16"	80841	2	BX67	20.47	
**20	AL16	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 18, 19, 20, 21	148594 ^F	2MVP80B94Q	1-5/8"	114045	2B5V110 ^G	1-7/16"	148605	2	BX69	20.53	
			AM 22, 23, 24	148593 ^E	2MVP70B84P	1-5/8"	148597	2B5V90 ^G	1-7/16"	114258	2	BX64	20.11	
			AM 17	148593 ^E	2MVP70B84P	1-5/8"	113811	2BK120H ^D	1-7/16"	80841	2	BX67		
			AM 18, 19, 20, 21	148594 ^F	2MVP80B94Q	1-5/8"	114045	2B5V110 ^G	1-7/16"	148605	2	BX69		
***15	AL15	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 22, 23, 24	148593 ^E	2MVP70B84P	1-5/8"	148597	2B5V90 ^G	1-7/16"	114258	2	BX64		
			AM 17	148593 ^E	2MVP70B84P	1-5/8"	113811	2BK120H ^D	1-7/16"	80841	2	BX67		
***20	AL16	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 18, 19, 20, 21	148594 ^F	2MVP80B94Q	1-5/8"	114045	2B5V110 ^G	1-7/16"	148605	2	BX69		
			AM 22, 23, 24	148593 ^E	2MVP70B84P	1-5/8"	148597	2B5V90 ^G	1-7/16"	114258	2	BX64		

*Distance between blower shaft and motor centerline with belts tensioned properly. ** Three-Groove Drives ***Two-Groove Drives

^A Use 1-3/16 "H" Blower Pulley Bushing, P/N 106260 ^E Use 1-5/8 "P2" Motor Pulley Bushing, P/N 148595

^B Use 1-3/16 "Q1" Blower Pulley Bushing, P/N 39460 ^F Use 1-5/8 "Q2" Motor Pulley Bushing, P/N 148596

^C Use 1-7/16 "H" Blower Pulley Bushing, P/N 89659 ^G Use 1-7/16 "P1" Blower Pulley Bushing, P/N 106261

^D Use 1-7/16 "B" Blower Pulley Bushing, P/N 114033

Drive Components for Totally Enclosed Motors

Unit Size	TEFC Motor		Voltage Option	Drive AM Nos. (See Key, pg 35)	Motor Pulley			Blower Pulley			Belt			*Shaft Centerline
	HP	Opt			P/N	Mfr #	Bore	P/N	Mfr #	Bore	P/N	Qty	Mfr #	
All "BL"	1	AL23	AK1 (115/1); AK2 (208/1); AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 2, 3, 4	13580	1VL34	5/8	111862	AK84	1-3/16	16134	1	A57	20.94
				AM 5, 6, 7	13580	1VL34	5/8	105484	AK71H ^C	1-3/16	16134	1	A57	21.03
	1-1/2	AL24	AK1 (115/1); AK2 (208/1); AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3)	AM 3, 4, 5, 6, 7	13580	1VL34	5/8	105484	AK71H ^C	1-3/16	16134	1	A57	21.03
				AM 8, 9, 10, 11	105476	1VL44	5/8	106256	AK74	1-3/16	16134	1	A57	21.11
				AM 3, 4, 5, 6, 7			7/8				16134	1	A57	21.03
				AM 8, 9, 10, 11			7/8				16134	1	A57	21.11
	2	AL25	AK1 (115/1); AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3)	AM 3, 4, 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^C	1-3/16	16132	1	A55	20.03
				AM 8, 9, 10, 11	106758	1VL44	7/8	105484	AK71H ^C	1-3/16	16133	1	A56	20.85
				AM 12, 13, 14, 15, 16	106758	1VL44	7/8	110807	AK56H ^C	1-3/16	16131	1	A54	21.07
				AM 7, 8, 9	37451	1VM50	7/8	16160	AK184	1-3/16	92264	1	A78	20.95
	3	AL26	AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 10, 11, 12, 13	106758	1VL44	7/8	16158	AK134	1-3/16	16558	1	A69	20.96
				AM 14, 15, 16, 17, 18	37451	1VM50	7/8	16156	AK124	1-3/16	111870	1	A66	20.92
				AM 7, 8, 9	37451	1VM50	7/8	16160	AK184	1-3/16	92264	1	A78	20.95
				AM 10, 11, 12, 13	106758	1VL44	7/8	16158	AK134	1-3/16	16558	1	A69	20.96

Unit Size	TEFC Motor		Drive AM Nos. (See Key, pg 35)	Motor Pulley			Blower Pulley			Belt			*Shaft	
	HP	Opt		P/N	Mfr #	Bore	P/N	Mfr #	Bore	P/N	Qty	Mfr #	Centerline	
All "BL" (cont'd)	5	AL27	AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 8, 9, 10, 11	7963	2VP42	1-1/8	16161	2AK134	1-3/16	16139	1	A67	21.08
				AM 12, 13, 14, 15	105581	2VP50	1-1/8	16161	2AK134	1-3/16	92408	1	A68	21.01
	AM 16, 17, 18, 19, 20	7963		2VP42	1-1/8	16003	2BK100	1-3/16	50477	1	A60	21.08		
	7-1/2	AL32		AM 10, 11	16150	2VP62	1-3/8	16138	2BK110	1-3/16	92414	1	B64	20.47
				AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31
				AM 14, 15, 16	16150	2VP62	1-3/8	91633	2TB86 ^A	1-3/16	92280	1	BX59	20.47
				AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^C	1-3/16	92280	1	BX59	20.37
	10	AL33		AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47
				AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31
				AM 14, 15, 16	16150	2VP62	1-3/8	91633	2TB86 ^A	1-3/16	92280	1	BX59	20.47
			AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^C	1-3/16	92280	1	BX59	20.37	
	**15 & 20	AL34 AL35	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	**AM 15, 16, 17	148593	2MVP70B84P ^E	1-5/8	113811	2BK120H ^D	1-7/16	80841	2	BX67	20.47
				**AM 18, 19, 20, 21	148594	2MVP80B94Q ^F	1-5/8	114045	2B5V110 ^G	1-7/16	148605	2	BX69	20.53
	**AM 22, 23, 24	148593		2MVP70B84P ^E	1-5/8	148597	2B5V90 ^G	1-7/16	114258	2	BX64	20.11		
	***15	AL34		***AM 15, 16, 17	148593 ^E	2MVP70B84P	1-5/8	113811	2BK120H ^D	1-7/16	80841	2	BX67	
				***AM 18, 19, 20, 21	148594 ^F	2MVP80B94Q	1-5/8	114045	2B5V110 ^G	1-7/16	148605	2	BX69	
				***AM 22, 23, 24	148593 ^E	2MVP70B84P	1-5/8	148597	2B5V90 ^G	1-7/16	114258	2	BX64	
	***20	AL35		***AM 17	148593 ^E	2MVP70B84P	1-5/8	113811	2BK120H ^D	1-7/16	80841	2	BX67	
				***AM 18, 19, 20, 21	148594 ^F	2MVP80B94Q	1-5/8	114045	2B5V110 ^G	1-7/16	148605	2	BX69	
				***AM 22, 23, 24	148593 ^E	2MVP70B84P	1-5/8	148597	2B5V90 ^G	1-7/16	114258	2	BX64	

*Distance between blower shaft and motor centerline with belts tensioned properly. ** Three-Groove Drives ***Two-Groove Drives

^A Use 1-3/16 "Q1" Blower Pulley Bushing, P/N 39460

^E Use 1-5/8 "P2" Motor Pulley Bushing, P/N 148595

^B Use 1-7/16 "P1" Blower Pulley Bushing, P/N 106261

^F Use 1-5/8 "Q2" Motor Pulley Bushing, P/N 148596

^C Use 1-3/16 "H" Blower Pulley Bushing, P/N 106260

^G Use 1-7/16 "B" Blower Pulley Bushing, P/N 114033

^D Use 1-7/16 "H" Blower Pulley Bushing, P/N 89659

Drive Components for Premium Efficiency Motors

Unit Size	Premium Motor		Voltage Option	Drive AM Nos. (See Key, page 35)	Motor Pulley			Blower Pulley			Belt			*Shaft
	HP	Opt			P/N	Mfr No.	Bore	P/N	Mfr No.	Bore	P/N	Qty	Mfr No.	Centerline
All "BL" Units	1	AL36	AK5 (208/3); AK6 (230/3); AK7 (460/3); AK8 (575/3)	AM 2, 3, 4	110125	1VP34	7/8	111862	AK84	1-3/16	16134	1	A57	20.94
				AM 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^A	1-3/16	16132	1	A55	21.03
	1-1/2	AL37		AM 3, 4, 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^A	1-3/16	16132	1	A55	21.03
				AM 8, 9, 10, 11	106758	1VL44	7/8	106256	AK74	1-3/16	16134	1	A57	21.11
				AM 3, 4, 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^A	1-3/16	16132	1	A55	20.03
	2	AL38		AM 8, 9, 10, 11	106758	1VL44	7/8	105484	AK71H ^A	1-3/16	16133	1	A56	20.85
				AM 12, 13, 14, 15, 16	106758	1VL44	7/8	110807	AK56H ^A	1-3/16	16131	1	A54	21.07
				AM 7, 8, 9	37451	1VM50	7/8	16160	AK184	1-3/16	92264	1	A78	20.95
	3	AL39		AM 10, 11, 12, 13	106758	1VL44	7/8	16158	AK134	1-3/16	16558	1	A69	20.96
				AM 14, 15, 16, 17, 18	37451	1VM50	7/8	16156	AK124	1-3/16	111870	1	A66	20.92
			AM 8, 9, 10, 11	7963	2VP42	1-1/8	16161	2AK134	1-3/16	16139	1	A67	21.08	
	5	AL40	AM 12, 13, 14, 15	105881	2VP50	1-1/8	16161	2AK34	1-3/16	92408	1	A68	21.01	
			AM 16, 17, 18, 19, 20	7963	2VP42	1-1/8	16003	2BK100	1-3/16	50477	1	A60	21.08	
			AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47	
	7-1/2	AL41	AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31	
			AM 14, 15, 16	16150	2VP62	1-3/8	91633	2TB86 ^B	1-3/16	92280	1	BX59	20.47	
			AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^A	1-3/16	92280	1	BX59	20.37	
	10	AL42	AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47	
			AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31	
			AM 14, 15, 16	16150	2VP62	1-3/8	91633	2TB86 ^B	1-3/16	92280	1	BX59	20.47	
AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^A	1-3/16	92280	1	BX59	20.37				
**15 & 20	AL43 AL44	**AM 15, 16, 17	148593	2MVP70B84P ^D	1-5/8	113811	2BK120H ^C	1-7/16	80841	2	BX67	20.47		
		**AM 18, 19, 20, 21	148594	2MVP80B94Q ^E	1-5/8	114045	2B5V110 ^F	1-7/16	148605	2	BX69	20.53		
**AM 22, 23, 24	148593	2MVP70B84P ^D	1-5/8	148597	2B5V90 ^F	1-7/16	114258	2	BX64	20.11				
***15	AL43	***AM 15, 16, 17	148593	2MVP70B84P ^D	1-5/8	113811	2BK120H ^C	1-7/16	80841	2	BX67			
		***AM 18, 19, 20, 21	148594	2MVP80B94Q ^E	1-5/8	114045	2B5V110 ^F	1-7/16	148605	2	BX69			
		***AM 22, 23, 24	148593	2MVP70B84P ^D	1-5/8	148597	2B5V90 ^F	1-7/16	114258	2	BX64			
***20	AL44	***AM 17	148593	2MVP70B84P ^D	1-5/8	113811	2BK120H ^C	1-7/16	80841	2	BX67			
		***AM 18, 19, 20, 21	148594	2MVP80B94Q ^E	1-5/8	114045	2B5V110 ^F	1-7/16	148605	2	BX69			
		***AM 22, 23, 24	148593	2MVP70B84P ^D	1-5/8	148597	2B5V90 ^F	1-7/16	114258	2	BX64			

*Distance between blower shaft and motor centerline with belts tensioned properly. ** Three-Groove Drives ***Two-Groove Drives

^A Use 1-3/16 "H" Blower Pulley Bushing, P/N 106260

^D Use 1-5/8 "P2" Motor Pulley Bushing, P/N 148595

^B Use 1-3/16 "Q1" Blower Pulley Bushing, P/N 39460

^E Use 1-5/8 "Q2" Motor Pulley Bushing, P/N 148596

^C Use 1-7/16 "H" Blower Pulley Bushing, P/N 89659

^F Use 1-7/16 "B" Blower Pulley Bushing, P/N 114033

Drives - Model Series RGBL, RPBL, PGBL and Blower Cabinet RBL (cont'd)

Drive Components for Two-Speed Motors

Unit Size	2-Spd Motor		Voltage Option	Drive AM Nos. (See Key, page 35)	Motor Pulley			Blower Pulley			Belt		*Shaft Centerline	
	HP	Opt			P/N	Mfr #	Bore	P/N	Mfr #	Bore	P/N	Qty		Mfr #
All "BL" Units	1	AL45	AK5 (208/3); AK6 (230/3); AK7 (460/3)	AM 2, 3, 4	110125	1VP34	7/8	111862	AK84	1-3/16	16134	1	A57	20.94
				AM 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^A	1-3/16	16132	1	A55	21.03
	1-1/2	AL46		AM 3, 4, 5, 6, 7	110125	1VP34	7/8	105484	AK71H ^A	1-3/16	16132	1	A55	21.03
				AM 8, 9, 10, 11	106758	1VL44	7/8	106256	AK74	1-3/16	16134	1	A57	21.11
	2	AL47		AM 4, 5	111681	1VP50	1-1/8	16156	AK124	1-3/16	111870	1	A66	20.92
				AM 6, 7, 8, 9	110151	1VP44	1-1/8	111862	AK84	1-3/16	92402	1	A59	21.28
	3	AL48		AM 10, 11, 12, 13	110151	1VP44	1-1/8	112026	BK85H ^A	1-3/16	92225	1	B57	21.22
				AM 14, 15, 16, 17, 18, 19	110151	1VP44	1-1/8	112035	BK60	1-3/16	92239	1	BX54	20.93
	5	AL49		AM 4, 5	111681	1VP50	1-1/8	16156	AK124	1-3/16	111870	1	A66	20.92
				AM 6, 7, 8, 9	110151	1VP44	1-1/8	111862	AK84	1-3/16	92402	1	A59	21.28
	7-1/2	AL50		AM 10, 11, 12, 13	110151	1VP44	1-1/8	112026	BK75H ^A	1-3/16	92225	1	B57	21.22
				AM 14, 15, 16, 17, 18, 19	110151	1VP44	1-1/8	112035	BK60	1-3/16	92239	1	BX54	20.93
	10	AL51		AM 8, 9, 10, 11	106257	2VP60	1-3/8	16168	2BK110	1-3/16	6010	1	B65	21.28
				AM 12, 13, 14, 15	106257	2VP60	1-3/8	16167	2BK90	1-3/16	92289	1	BX61	20.93
	10	AL51		AM 16, 17, 18, 19, 20	106257	2VP60	1-3/8	92419	2TB70 ^B	1-3/16	16143	1	B59	21.07
				AM 10, 11	16150	2VP62	1-3/8	16168	2BK110	1-3/16	92414	1	B64	20.47
	10	AL51		AM 12, 13	16150	2VP62	1-3/8	16003	2BK100	1-3/16	7950	1	B62	20.31
				AM 14, 15, 16	16150	2VP62	1-3/8	91633	2TB86 ^B	1-3/16	92280	1	BX59	20.47
	10	AL51		AM 17, 18, 19, 20	110771	2VP65	1-3/8	89648	2BK80H ^A	1-3/16	92280	1	BX59	20.37
				AM 13, 14, 15, 16	91615	2MPV40-B54	1-5/8	89648	2BK80H ^A	1-3/16	92226	1	B58	20.47
10	AL51	AM 17, 18, 19, 20, 21, 22	91615	2MPV40-B54	1-5/8	110810	2BK70H ^A	1-3/16	92225	1	B57	20.37		

*Distance between blower shaft and motor centerline with belts tensioned properly.

^A Use 1-3/16 "H" Blower Pulley Bushing, P/N 106260.

^B Use 1-3/16 "Q1" Blower Pulley Bushing, P/N 39460.

Drive Table for Model RBHA

Open Motor HP	Opt	Voltage Option	Drive AM Nos. (See Key, page 35)	Motor Pulley			Blower Pulley			Belt		*Shaft Centerline	
				P/N	Mfr #	Bore	P/N	Mfr #	Bore	P/N	Qty		Mfr #
1/4	AL2	AK1 (115/1); AK2 (208/1); AK3 (230/1); AK5 (208/3); AK6 (230/3); AK7 (460/3)	AM 1, 2	4074	1VL34	1/2	111609	AK99	1	88560	1	A61	21.16
			AM 3, 4	4074	1VL34	1/2	19111	AK84	1	50476	1	A58	20.94
1/3	AL3		AM 1, 2	4074	1VP34	1/2	111609	AK99	1	88560	1	A61	21.16
			AM 3, 4	4074	1VP34	1/2	19111	AK84	1	50476	1	A58	20.94
1/2	AL4		AM 5, 6, 7	4074	1VP34	1/2	18797	AK64	1	16132	1	A55	21.11
			AM 1, 2	13580	1VL34	5/8	111609	AK99	1	16137	1	A62	21.66
3/4	AL5		AM 3, 4, 5	105476	1VL44	5/8	16153	AK104	1	80836	1	A64	21.59
			AM 6, 7, 8	13580	1VL34	5/8	18797	AK64	1	16133	1	A56	21.61
1	AL6		AM 9, 10, 11	13013	1VM50	5/8	19111	AK84	1	88560	1	A61	21.34
			AM 12, 13, 14, 15, 16, 17, 18	7962	1VL40	5/8	111689	AK49	1	16131	1	A54	21.44
1	AL6		AM 5, 6, 7	13013	1VM50	5/8	16153	AK104	1	111870	1	A66	22.16
			AM 8, 9, 10, 11	13013	1VM50	5/8	19111	AK84	1	88560	1	A61	21.34
1-1/2	AL7		AM 12, 13, 14, 15, 16, 17, 18	7962	1VL40	5/8	111689	AK49	1	16131	1	A54	21.44
			AM 19, 20, 21, 22, 23	105476	1VL44	5/8	105481	AK46	1	16131	1	A54	21.37
2	AL8		AM 5, 6, 7			7/8				111870	1	A66	22.16
			AM 8, 9, 10, 11			7/8				88560	1	A61	21.34
2	AL8		AM 12, 13, 14, 15, 16, 17, 18	7962	1VL40	5/8	111689	AK49	1	16131	1	A54	21.44
			AM 19, 20, 21, 22, 23	105476	1VL44	5/8	105481	AK46	1	16131	1	A54	21.37
3	AL9		AM 11, 12, 13, 14, 15			5/8				16145	1	B58	21.54
			AM 16, 17, 18, 19			5/8				50477	1	A60	21.57
5	AL10	AM 20, 21, 22, 23			5/8				111870	1	A66	22.17	
		AM 11, 12, 13, 14, 15	106758	1VL44	7/8	101414	BK130	1	16145	1	B58	21.54	
5	AL10	AM 16, 17, 18, 19	106748	1VL40	7/8	19111	AK84	1	50477	1	A60	21.57	
		AM 20, 21, 22, 23	37451	1VM50	7/8	16153	AK104	1	111870	1	A66	22.17	
5	AL10	AM 13, 14, 15, 16, 17	87500	2VP36	7/8	89649	2BK100H ^A	1	92411	1	BX62	21.54	
		AM 18, 19, 20, 21, 22, 23, 24	6599	2VP42	7/8	87504	2AK84	1	50477	1	A60	21.43	

*Distance between blower shaft and motor centerline with belts tensioned properly.

^A Use 1" x H Blower Pulley Bushing, P/N 92203